

# ArubaOS-Switch MIB and Trap Support Matrix

**aruba**

a Hewlett Packard  
Enterprise company

Part Number: 5200-4838  
Published: July 2018  
Edition: 1

## Notices

The information contained herein is subject to change without notice. The only warranties for Hewlett Packard Enterprise products and services are set forth in the express warranty statements accompanying such products and services. Nothing herein should be construed as constituting an additional warranty. Hewlett Packard Enterprise shall not be liable for technical or editorial errors or omissions contained herein.

Confidential computer software. Valid license from Hewlett Packard Enterprise required for possession, use, or copying. Consistent with FAR 12.211 and 12.212, Commercial Computer Software, Computer Software Documentation, and Technical Data for Commercial Items are licensed to the U.S. Government under vendor's standard commercial license.

Links to third-party websites take you outside the Hewlett Packard Enterprise website. Hewlett Packard Enterprise has no control over and is not responsible for information outside the Hewlett Packard Enterprise website.

## Acknowledgments

Intel<sup>®</sup>, Itanium<sup>®</sup>, Pentium<sup>®</sup>, Xeon<sup>®</sup>, Intel Inside<sup>®</sup>, and the Intel Inside logo are trademarks of Intel Corporation in the U.S. and other countries.

Microsoft<sup>®</sup> and Windows<sup>®</sup> are either registered trademarks or trademarks of Microsoft Corporation in the United States and/or other countries.

Adobe<sup>®</sup> and Acrobat<sup>®</sup> are trademarks of Adobe Systems Incorporated.

Java<sup>®</sup> and Oracle<sup>®</sup> are registered trademarks of Oracle and/or its affiliates.

UNIX<sup>®</sup> is a registered trademark of The Open Group.

**Chapter 1 Supported MIBs and Traps..... 4**

**Chapter 2 Websites..... 11**

**Chapter 3 Support and other resources..... 12**

- Accessing Hewlett Packard Enterprise Support..... 12
- Accessing updates..... 12
- Customer self repair..... 13
- Remote support..... 13
- Warranty information..... 13
- Regulatory information..... 14
- Documentation feedback..... 14

The following table contains the MIBs and Traps supported for each software feature in ArubaOS-Switch. The minimum software version is provided along with the feature name.

Software Feature (minimum software version)	MIBs Supported	Traps Supported
100 Mbps Support on Smart Rate ports (16.06)	hpSwitchConfig hpSwitchPortFastEtherMode	N/A
1588 PTP (16.04)	hpSwitchConfig	N/A
2930F VSF with 8 Members (16.06)	hpicfVsfVC	hpicfVsfVCCommanderChange hpicfVsfVCMemberChange hpicfVsfVCMemberStatusChange
ACL grouping (16.01)	hpicfGppcv2	N/A
ACL Logging Match (16.02)	hpicfDebugLog	N/A
Activate firmware upgrade (16.03)	hpicfActivate	N/A
Add MTU to Device Profile (16.02)	hpicfDevConf	N/A
Advanced Threat Detection (16.05)	hpicfBasic hpicfSyslog	N/A
Allow Unsupported Transceiver (16.02)	hpicfTransceiver	N/A
ARP Throttling (16.01)	hpicfArpThrottle	hpicfArpThrottleExceedThresholdTrap
ArubaMAS (16.01)	hpicfDevConf	N/A
BFD (16.01)	hpicfBfd hpicfVrrp hpicfOspf ianabfdStd rfc7330.mibrfc7331	N/A
BFD on static router (16.04)	hpicfIpRoute hpicfBfd	N/A

*Table Continued*

Software Feature (minimum software version)	MIBs Supported	Traps Supported
Bonjour (16.01)	hpicfMdns	N/A
Clear DHCP snooping binding (16.03)	hpicfDhcpSnoop	N/A
Client static IP visibility (16.03)	hpicfIpAddress	N/A
Configurable Threshold Value for SNMP Traps (16.06)	hpSwitchConfig hpicfSwitchRMONLogThreshold	N/A
Configure backup and restore without reboot (16.05)	hpicfConfig	N/A
Configuring Traffic Templates (16.05)	hpicRateLimit hpicfTrafficTemplate	N/A
Connected Devices Reporting (16.04)	hpicfIpAddress	N/A
Console lockout (16.06)	hpicfAuth hpSwitchAuthConsoleLockout	N/A
Critical roles (16.05)	hpicfDot1x	N/A
DHCPv6 snooping (16.05)	hpicfSavi hpicfDSnoopV6	hpicfDSnoopV6SourceBindingOutOfResources hpicfDSnoopV6SourceBindingErrantReply
Device Fingerprinting with Aruba ClearPass (16.06)	hpicfDeviceMonitor	N/A
DIPLDv6 (16.05)	hpicfSavi hpicfDipldv6	hpicfDIPDv6SourceBindingOutOfResources hpicfDIPLDv6SourceBindingViolations
Downloadable User Roles (16.04)	hpicfAutz hpicfAuth	N/A
Dynamic OUI based device profiling (16.04)	hpicfDevConf hpicfDeviceIdentity	N/A
Federal Government Certifications (16.03)	hpicfAuth hpSwitchConfig hpicfKeyMin hpicfSyslog	N/A

*Table Continued*

Software Feature (minimum software version)	MIBs Supported	Traps Supported
Federal Government Certifications: SSH-Rekey (16.04)	hpicfAuth hpSwitchConfig	N/A
Federal Government Certifications: TLS version enforcement for Cloud applications (16.03)	hpicfTlsMin	N/A
Federal Government Certifications: User lockout (16.04)	Added to hpicfAuth: <ul style="list-style-type: none"> <li>hpicfSwitchUnlockUser</li> <li>hpicfSwitchUserBasedLockout</li> </ul>	N/A
FIPS-140 (16.02)	hpicfAuthhpicfNtp	N/A
FQDN support for NTP server (16.05)	hpicfNtp	N/A
Front Panel Security (16.05)	hpicfAuth	N/A
Global OSPF cost setting (16.05)	hpicfOspf hpicfOspfv3	N/A
Hibernation (16.04)	hpSwitchConfig	N/A
Infra : Feature Preview mode (16.01)	hpSwitchConfig	N/A
IP Service Level Agreement (SLA) (16.02)	hpicfIpSla	hpicfIpSlaThresholdExceeded hpicfIpSlaTestCompletion hpicfIpSlaThresholdPktLoss
IP SLA - DNS and DHCP SLA, UDP jitter and VoIP SLA (16.03)	hpicfIpSla	N/A
IPsec for AirWave Connection (16.02)	hpicfAMPServer	N/A
IPSec tunnel to secondary controller (16.06)	hpicfAMPServer hpicfArubaVPNBkpIPType hpicfArubaVPNBkpIP	N/A
IPv6 router preference (16.04)	hpicfIpRoute	N/A

Table Continued

Software Feature (minimum software version)	MIBs Supported	Traps Supported
IPv6 ZTP for Dataport (16.06)	hpicfAMPServer hpicfAMPServerIPType. hpicfAMPServerIP hpicfAMPServerGroup hpicfAMPServerFolder hpicfAMPServerSecret hpicfAMPServerConfigStatus	N/A
JSON / REST API (16.01)	hpSwitchBasicConfig	N/A
Local User Roles (16.02)	hpicfAutz hpicfLma hpicfDot1x hpicfGppcv2 hpicfUsrAuth	N/A
Log Blackhole/NULL Route (16.02)	hpicflpRoute	N/A
MAC age (16.05)	hpicfGenericVlan	N/A
MAC Authentication Toggle (16.02)	hpicfUsrAuth	N/A
MAC delimiter (16.04)	hpSwitchConfig	N/A
Mac pinning (16.05)	hpicfUsrAuth hpicfLma	N/A
Management module preference (16.04)	hpicfHighAvailability	N/A
MAS: LLDAP authentication bypass with AP (16.02.0012)	hpicfUsrAuth	N/A
MVRP (16.01)	hpicfMvrp ieee8021Bridge ieee8021qbridge	hpicfMvrpVlanLimitReachedEvent

*Table Continued*

Software Feature (minimum software version)	MIBs Supported	Traps Supported
Multicast Storm control (16.06)	<pre> hpicfFfMcastStormPortConfig HpicfFfMcastStormPortConfigEntry : := SEQUENCE { hpicfFfMcastStormPortIndex hpicfFfMcastStormMode hpicfFfMcastStormRisingpercent hpicfFfMcastStormRisingpps hpicfFfMcastStormAction hpicfFfMcastStormPortDisablTimer } </pre>	N/A
Net-destination (16.06)	hpicfGppcv2PrPolicyRule	N/A
New CLI: dhcp-snooping-allow-overwrite-binding (16.02)	hpicfDhcpSnoop	N/A
New CLI: ipv6 mld send-router-alert alternative-padding (16.02)	hpicfMld	N/A
New CLI: power-over-ethernet poe-reset port a5 (16.02)	hpicfPoe	N/A
NTP (16.01)	hpicfNtp rfc5907	N/A
Open authentication (16.05)	hpicfDot1x	N/A
OpenFlow — Custom Matches (16.02)	hpicfOpenFlow	N/A
OSPF Routed Access Support (16.02)	hpicfOspf	N/A
Password Complexity (16.01)	hpicfAuth	hpSwitchPasswordExpiryNotify
Per-Port Initial Role (16.05)	hpicfDot1x	N/A
Per Port Trust (16.02)	hpSwitchConfig	N/A
Per Port Tunneled Node (16.02)	hpicfTunneledNode	N/A
Per User Tunnel (16.04)	hpicfTunneledNode	N/A

Table Continued



Software Feature (minimum software version)	MIBs Supported	Traps Supported
PIMv6 (16.05)	hpicfPim6	hpicfPim6TrapControl hpicfPim6HardMRTFull hpicfPim6SoftMRTFull
Port automatic 3rd party device detection (16.03)	hpicfDevConf	N/A
Preventing double tunneling of Aruba Access Points (16.05)	hpicfDevConf	N/A
Private VLAN (16.01)	hpicfPrivateVlan	N/A
RADIUS availability (16.01)	hpicfAuth	N/A
RADIUS tracking (16.05)	hpicfAuth	N/A
RADIUS tracking (16.06)	hpicfAuth hpSwitchRadiusTrackingPassword hpSwitchRadiusTrackDeadOnly hpSwitchRadiusTrackReqPktCount	N/A
Resilient 802.1x cached-reauth (16.05)	hpicfDot1x	N/A
Retain Configuration on 5400R when Switching from v3-only to v2-compatible mode (16.02)	hpSwitchConfig	N/A
RIPng (16.01)	hpicfRipng	hpicfRipngIfStateChange hpicfRipngIfConfigError hpicfRipngIfRxBadPacket
Schedule Job (16.01)	hpicfJobScheduler	N/A
SNMP Port Egress Queue (16.06)	hpSwitchEgressQueueTxPkts hpSwitchEgressQueueTxDropPkts hpSwitchEgressQueueTxBytes hpSwitchEgressQueueTxDropBytes	N/A
Source IP specification for OpenFlow (16.05)	hpicfOpenFlow	N/A
TLS Cipher-Disable (16.04)	hpicfTlsMin	N/A
Traffic Policing with the Two Rate Three Color Marker	hpicfGppcv2PrPolicyRule	N/A

*Table Continued*

Software Feature (minimum software version)	MIBs Supported	Traps Supported
Tunnel node fallback to switching (16.02.0012)	hpicfTunneledNode	N/A
VSF (16.01)	hpicfVsfVC	hpicfVsfVCCommanderChange hpicfVsfVCMemberChange hpicfVsfVCMemberStatusChange
VSF 4-member chain, 1G inter-link support, basic traffic forwarding (Unicast only) (16.03)	hpicfVsfVC	N/A
VSF 4-member ring, topology change, HA, stack split, plug and play, multi-homed trunks, multicast forwarding (16.03)	hpicfVsfVC	N/A

### Networking Websites

Hewlett Packard Enterprise Networking Information Library

[www.hpe.com/networking/resourcefinder](http://www.hpe.com/networking/resourcefinder)

Hewlett Packard Enterprise Networking Software

[www.hpe.com/networking/software](http://www.hpe.com/networking/software)

Hewlett Packard Enterprise Networking website

[www.hpe.com/info/networking](http://www.hpe.com/info/networking)

Hewlett Packard Enterprise My Networking website

[www.hpe.com/networking/support](http://www.hpe.com/networking/support)

Hewlett Packard Enterprise My Networking Portal

[www.hpe.com/networking/mynetworking](http://www.hpe.com/networking/mynetworking)

Hewlett Packard Enterprise Networking Warranty

[www.hpe.com/networking/warranty](http://www.hpe.com/networking/warranty)

### General websites

Hewlett Packard Enterprise Information Library

[www.hpe.com/info/EIL](http://www.hpe.com/info/EIL)

For additional websites, see [Support and other resources](#).

## Accessing Hewlett Packard Enterprise Support

- For live assistance, go to the Contact Hewlett Packard Enterprise Worldwide website:  
<http://www.hpe.com/assistance>
- To access documentation and support services, go to the Hewlett Packard Enterprise Support Center website:  
<http://www.hpe.com/support/hpesc>

### Information to collect

- Technical support registration number (if applicable)
- Product name, model or version, and serial number
- Operating system name and version
- Firmware version
- Error messages
- Product-specific reports and logs
- Add-on products or components
- Third-party products or components

## Accessing updates

- Some software products provide a mechanism for accessing software updates through the product interface. Review your product documentation to identify the recommended software update method.
- To download product updates:
  - Hewlett Packard Enterprise Support Center**  
[www.hpe.com/support/hpesc](http://www.hpe.com/support/hpesc)
  - Hewlett Packard Enterprise Support Center: Software downloads**  
[www.hpe.com/support/downloads](http://www.hpe.com/support/downloads)
  - Software Depot**  
[www.hpe.com/support/softwaredepot](http://www.hpe.com/support/softwaredepot)
- To subscribe to eNewsletters and alerts:  
[www.hpe.com/support/e-updates](http://www.hpe.com/support/e-updates)
- To view and update your entitlements, and to link your contracts and warranties with your profile, go to the Hewlett Packard Enterprise Support Center **More Information on Access to Support Materials** page:



---

**IMPORTANT:** Access to some updates might require product entitlement when accessed through the Hewlett Packard Enterprise Support Center. You must have an HPE Passport set up with relevant entitlements.

---

## Customer self repair

Hewlett Packard Enterprise customer self repair (CSR) programs allow you to repair your product. If a CSR part needs to be replaced, it will be shipped directly to you so that you can install it at your convenience. Some parts do not qualify for CSR. Your Hewlett Packard Enterprise authorized service provider will determine whether a repair can be accomplished by CSR.

For more information about CSR, contact your local service provider or go to the CSR website:

<http://www.hpe.com/support/selfrepair>

## Remote support

Remote support is available with supported devices as part of your warranty or contractual support agreement. It provides intelligent event diagnosis, and automatic, secure submission of hardware event notifications to Hewlett Packard Enterprise, which will initiate a fast and accurate resolution based on your product's service level. Hewlett Packard Enterprise strongly recommends that you register your device for remote support.

If your product includes additional remote support details, use search to locate that information.

### Remote support and Proactive Care information

#### HPE Get Connected

[www.hpe.com/services/getconnected](http://www.hpe.com/services/getconnected)

#### HPE Proactive Care services

[www.hpe.com/services/proactivecare](http://www.hpe.com/services/proactivecare)

#### HPE Proactive Care service: Supported products list

[www.hpe.com/services/proactivecaresupportedproducts](http://www.hpe.com/services/proactivecaresupportedproducts)

#### HPE Proactive Care advanced service: Supported products list

[www.hpe.com/services/proactivecareadvancedsupportedproducts](http://www.hpe.com/services/proactivecareadvancedsupportedproducts)

### Proactive Care customer information

#### Proactive Care central

[www.hpe.com/services/proactivecarecentral](http://www.hpe.com/services/proactivecarecentral)

#### Proactive Care service activation

[www.hpe.com/services/proactivecarecentralgetstarted](http://www.hpe.com/services/proactivecarecentralgetstarted)

## Warranty information

To view the warranty information for your product, see the links provided below:

#### HPE ProLiant and IA-32 Servers and Options

[www.hpe.com/support/ProLiantServers-Warranties](http://www.hpe.com/support/ProLiantServers-Warranties)

#### HPE Enterprise and Cloudline Servers

[www.hpe.com/support/EnterpriseServers-Warranties](http://www.hpe.com/support/EnterpriseServers-Warranties)

## HPE Storage Products

[www.hpe.com/support/Storage-Warranties](http://www.hpe.com/support/Storage-Warranties)

## HPE Networking Products

[www.hpe.com/support/Networking-Warranties](http://www.hpe.com/support/Networking-Warranties)

# Regulatory information

To view the regulatory information for your product, view the *Safety and Compliance Information for Server, Storage, Power, Networking, and Rack Products*, available at the Hewlett Packard Enterprise Support Center:

[www.hpe.com/support/Safety-Compliance-EnterpriseProducts](http://www.hpe.com/support/Safety-Compliance-EnterpriseProducts)

## Additional regulatory information

Hewlett Packard Enterprise is committed to providing our customers with information about the chemical substances in our products as needed to comply with legal requirements such as REACH (Regulation EC No 1907/2006 of the European Parliament and the Council). A chemical information report for this product can be found at:

[www.hpe.com/info/reach](http://www.hpe.com/info/reach)

For Hewlett Packard Enterprise product environmental and safety information and compliance data, including RoHS and REACH, see:

[www.hpe.com/info/ecodata](http://www.hpe.com/info/ecodata)

For Hewlett Packard Enterprise environmental information, including company programs, product recycling, and energy efficiency, see:

[www.hpe.com/info/environment](http://www.hpe.com/info/environment)

# Documentation feedback

Hewlett Packard Enterprise is committed to providing documentation that meets your needs. To help us improve the documentation, send any errors, suggestions, or comments to Documentation Feedback ([docsfeedback@hpe.com](mailto:docsfeedback@hpe.com)). When submitting your feedback, include the document title, part number, edition, and publication date located on the front cover of the document. For online help content, include the product name, product version, help edition, and publication date located on the legal notices page.